



DADC-144DT

Order No.: 0257910

PRODUCTINFOS

4-channel Dante® transceiver

- 4 analogue XLR audio inputs
- 4 analogue XLR audio outputs
- 4-channel Dante® input/output (EtherCon/RJ45)
- Analogue input and output levels can be adjusted individually via recessed potentiometers
- 48 V phantom power can be activated as required for each analogue input
- Mute function for each analogue output
- Dante® sources and Dante® receiver can be combined via software
- Encoding/decoding: 16/24/32 bits
- Sampling rates: 44.1/48/88.2/96 kHz
- Frequency range: 20-20,000 Hz
- LED display for indicating signal, peak, network link, network act and power
- Metal housing
- 482 mm (19") rack installation, 1 RS

The brand Dante® as well as the Dante® software which may have been integrated into these products are licenced by Audinate Pty Ltd.

TECHNICAL SPECIFICATIONS

DADC-144DT

Description	4-channel Dante® transceiver
Frequency range	20-20,000 Hz

DADC-144DT

Input signal	2.3 V max.
Input sensitivity	5.7 mV-2.3 V
Gain	0.2-5.2x
Phantom power	48 V
S/N ratio	> 90 dB
THD	< 0.005%
Admiss. ambient temp.	0-40 °C
Power supply	230 V/50 Hz/15 VA
Dimensions	482 x 44.5 x 238 mm, 1 RS
Weight	2.9 kg
Inputs	4 x XLR, bal.
Outputs	4 x XLR, bal.
Other features	1 x EtherCon/RJ45

DADC-144DT

Resolution	16/24/32 bits
------------	---------------