

Mixing Preampfier Zone Router

Stereo mixing preamplifiers for background music and voice.

iMIX 5

Zone router with 5 stereo outputs for multi-zone audio control. iMix5 has 4 audio source inputs, which can be routed to any of 5 available outputs. Sources at individual zones can be selected by zone selector on front panel, using wall plate controller or RS232 commands. IMix5 has internal media player with USB, Bluetooth, FM receiver and AUX input. Priority input and external mute connectors for emergency audio installations.

Page station MIC iMIX is designed for zone paging.



MIC iMIX pagestation and WC iMIX touchpads should be ordered separately.

Technical Specifications	iMIX5
Inputs	Line inputs: 3 x stereo phoenix, sensitivity -12.5dBV Mic input: 1 x XLR, sensitivity -41dBV Call station input: 1 x RJ45, sensitivity +4dBV
Outputs	5 x stereo phoenix, rated 600 ohm 1 x XLR for zone monitoring
EMG input: SN ratio to microphone input SN ratio to line input	Sensitivity -10dBV 65dB 73dB
Media player	USB / Bluetooth / FM radio / AUX input
Phantom power	+24V DC
Frequency response	±3dB 20Hz - 20kHz
THD +N	<0.1% @ 1kHz
Controller inputs	RS232 interface 5 x RJ45 connectors for wall plate controllers
Power supply	100-240Vac, 50/60Hz
Dimensions	483 x 177 x 44mm
Weight	1.76kg