

COMMUNICATION AMPLIFIERS

iCOMC Communication Amplifiers

Two channel communication amplifiers with RS232 interface and IR remote control.

iCOMC 2X20

Mini D-class iCOMC amplifier 2x20 W with RS232 interface. 2 line and 1 microphone input, 2x20 W and 40 W bridge mode, tone control, phantom powered, LED source indication. Various input connectors to choose: RCA, Phoenix and 3.5 TRS jack. Signal source selection can be made by control button, RS232 command or IR remote control which can be purchased optionally. Mounting brackets are included into each package. Perfect device for small size installations where compact and user friendly device is necessary with possibility of remote control.



Optional accessory - IR re

| Technical Specifications | iCOMC 2X20 |
|--------------------------|--|
| Output power | 2 x 20 W |
| Power supply | 24 V DC 1,5 A |
| Outputs | Low impedance output - 4 Ω (screw terminal block) |
| Inputs | Mic: Sensitivity -60 dBu Connector - Balanced Phoenix Line 1: Sensitivity -7 dBu Connector - 3,5 mm stereo Jack Line 2: Sensitivity -7 dBu Connector - Stereo RCA |
| Frequency response | 35 Hz - 20 kHz |
| THD | < 0,03 % |
| Signal / noise ratio | > 100 dB |
| Tone control | Bass ± 7 dBu , Treble ± 7 dBu |
| Controls | Mic and Line input level controls, balance control, tone control, input selector, loudness, limiter and phantom power. RS 232 and IR remote controls. |
| Indicators | Power, volume, balance, tone |
| Dimensions | 145 mm x 120 mm x 45 mm |
| Weight | 0,6 kg |
| Colour | Black (RAL 9017) |