

MICROPHONES

# Paging Microphone

5 zone paging station for iMIX5 zone router.

## MIC iMIX

Five zone paging microphone with intuitive control buttons for iMIX5. Pressing selected zone button or all zone button enables to make announcements to selected zone or all zones together. Its possible to start talk immediately or make a chime first. Chime options can be selected with DIP switches.

Local audio source can be connected by TRS jack input.



Technical Specifications	MIC iMIX
Microphone type	Condenser microphone
Polar pattern	Cardioid
Frequency response	-3dB 150Hz - 22kHz
Control	6 x illuminated zone select buttons (1-5, all zones) 1 x Talk button
Input impedance	Mic: 600 Ohms, Aux: 50k Ohms
Output impedance	Balanced 600 Ohms
Input level Mic	-46dBV, Aux: -10dBV
Output level	10dBV
S/N ratio	-60dB
Connectors	RJ45, 24VDC power jack, 3.5mm stereo TRS
Interface	RS-485
Max. connection length	500m
Power supply	24Vdc, 500mA
Dimensions	460 mm x 140 mm x 115mm
Weight	670 g