


AT-58 ISM 5 GHz Multi-function Directional Antenna

Features

- Its built-in booster can increase the antenna gain levels for effectively compensating the signal loss of the coaxial cable. Provides an optimized signal transmission in long-distance for the ISM 5 GHz frequency band.



Specifications

| | |
|------------------|--|
| Frequency Range | ISM 5 GHz |
| Antenna Gain | 10 dBi |
| Built-in Booster | Built-in 20 dB booster |
| Connectors | TNC female × 2 |
| Power Supply | 10 ~ 24 V DC |
| Impedance | 50 Ω |
| Dimensions | 162 × 138 × 40 mm (W×H×D) |
| Weight | Approx. 270 g |
| Note | Refer to the actual product in the event of product description discrepancy. |