


# MPB-58 5 GHz Antenna Booster

## Features

- It is optimized in the ISM 5 GHz band to amplify the antenna signal, offering 20 dB gain to compensate for signal loss over long antenna cables and to increase the reception range and signal stability.
- The antenna booster can be powered by the bias of the receiver's antenna connector or by an external power supply, allowing longer antenna cables can be connected with more boosters.
- With an aluminum casing, it features superb heat dissipation and waterproof.



## Specifications

Frequency Range	5 GHz
Gain	Fixed, approx. 20 dB
Input / Output Connectors	1-to-1 TNC. 50 $\Omega$ Impedance.
Input Power	10 ~ 24 V DC
Regulated Power Output	Equals to the bias
Dimensions	41 × 80 × 24 mm (W×H×D)
Weight	Approx. 260 g
Note	Refer to the actual product in the event of product description discrepancy.