



DMP-130MIXBT

Order No.: 1000062

PRODUCTINFOS

MP3 player and microphone line mixer

With this unit combination, it is possible to mix 3 audio signal sources. The integrated MP3 player can be switched between SD card, USB port and Bluetooth receiver.

- For USB and SD storage media
- Alphanumeric display
- Repeat function
- Preprogrammed sound adjustments
- 3 input channels with level control (mic, aux/MP3, line)
- Aux input and microphone input via front panel connection
- 2-way tone control and level control for the master output
- Infrared remote control for MP3 player
- Blue backlit LCD
- 482 mm (19") rack installation

TECHNICAL SPECIFICATIONS

DMP-130MIXBT

Description	MP3 player and microphone line mixer
Media	MP3, USB, SD, MMC
Frequency range	20-20,000 Hz
THD	< 0.1%
Channel separation	> 60 dB
Dynamic range	> 96 dB
S/N ratio	> 70 dB

DMP-130MIXBT

Output, analogue	2 V (XLR, bal.)
	1 V (RCA)
Power supply	~ 230 V/50 Hz/20 VA
Mains voltage	~ 230 V
Mains frequency	50 Hz
Power consumption, operation	20 VA
Admiss. ambient temp.	0-40 °C
Dimensions	482 x 44 x 165 mm, 1 RS
Weight	2.36 kg
Connections	1 x combo 6.3 mm/XLR (mic/line),
	1 x 3.5 mm jack (aux in),
	1 x RCA L/R (line in),
	1 x RCA L/R (line out),
	1 x XLR L/R, bal. (output)
Packing dimensions (W x H x L)	0.55 x 0.12 x 0.2 m
Gross weight	2.74 kg